

Total No. of Questions : 10]

SEAT No. :

P1732

[Total No. of Pages : 3

[5460] - 561

T.E. (Electrical)

ADVANCED MICROCONTROLLER AND ITS APPLICATIONS
(2015 Pattern) (Semester - I)

Time : 2½ Hours]

[Max. Marks :70

Instructions to the candidates:

- 1) *Answers Q.1 or Q.2, Q.3 or Q.4, Q.5 or Q.6, Q.7 or Q.8, Q.9 or Q.10.*
- 2) *Figures to the right indicate full marks.*

- Q1)** a) Write an assembly language program for PIC 18 microcontroller to clear the contents of location 0×200 and 0×300 in internal data memory. [6]
- b) Draw the status register for the PIC microcontroller and explain the function of Digit Carry flag. [4]

OR

- Q2)** a) Explain the following instructions. [6]
- i) `MOVF 0 x 04,0,1`
 - ii) `MOVFF fs, fd`
 - iii) `BSF PORTD, 0`
- b) Write a program in C language to configure bits RD0 and RB0 as input bits. [4]

- Q3)** a) Explain any three addressing modes used in PIC 18 microcontroller. [6]
- b) Write an assembly language program for PIC 18 microcontroller to add 3 decimal numbers 1, 2, 3 and store the result in a location 0×040 in internal data memory. [4]

OR

P.T.O.

Q4) a) Draw T0CON register and explain function of individual bits of T0CON register. [6]

b) Find timer clock frequency and timer period for a PIC18 microcontroller with a crystal frequency of 16 MHz. Assume a pre scalar of 64 is used. [4]

Q5) a) Write a program in C language to configure CCP module of PIC18 microcontroller in PWM mode to generate a digital waveform with 40% duty cycle and 10 kHz frequency assuming PIC 18 microcontroller is running with 32 MHz crystal frequency. Use a pre scalar of 4 for timer2. [8]

b) Draw CCP1CON and list the steps involved in programming PIC microcontroller in Compare mode. [8]

OR

Q6) a) Explain how time period and duty cycle is set for generation of a waveform using PWM mode in CCP module in PIC 18 microcontroller. [8]

b) Draw CCP1CON and list the steps involved in programming PIC microcontroller in capture mode. [8]

Q7) a) Draw an interfacing diagram of LCD (16 × 2) with PIC18 microcontroller and explain the functions of various pins of LCD. [8]

b) Explain the interrupt structure of PIC18 microcontroller. [9]

OR

Q8) a) Write a neat diagram and flowchart explain AC voltage measurement using PIC microcontroller. [8]

b) Write a program in C language for PIC 18 microcontroller to transfer a letter 'T' serially and continuously at a baud rate of 9600. Use BRGH = 0. Assume crystal frequency = 10 MHz. [9]

Q9) a) With the help of interfacing diagram and flowchart explain how PIC 18 microcontroller can be used to measure temperature using LM35 sensor. [8]

- b) Explain with a neat diagram, interfacing of DAC 0808 with PIC microcontroller and write a program in C language for generation of Square waveform using DAC interfaced with PIC microcontroller through Port B. Use suitable delay. Assume the crystal frequency to be 10 MHz.[9]

OR

- Q10) a) Explain in detail the functions of following flags related to onboard ADC of PIC microcontroller [8]

- i) ADIF
- ii) Go/Done
- iii) ADFM
- iv) ADON

- b) With the help of a neat interfacing diagrams explain interfacing of an electromagnetic relay and an Optoisolator with a PIC18 microcontroller.[9]

