

Total No. of Questions : 4]

SEAT No. :

PA-1682

[Total No. of Pages : 2

[5931]-1905

First Year Engineering (All Branches)
BASIC ELECTRICAL ENGINEERING
(2019 Pattern) (Semester - I) (103004)

Time : 1 Hour]

[Max. Marks : 30

Instructions to the candidates:

- 1) *Solve Q.1 or Q.2, Q.3 or Q.4.*
- 2) *Figures to the right indicate full marks.*
- 3) *Neat diagrams must be drawn wherever necessary.*
- 4) *Assume suitable additional data, if necessary.*
- 5) *Use of non-programmable calculator is allowed.*

- Q1) a)** What is magnetic effect of an electric current in case of a long straight conductor? Hence state right hand thumb rule. [3]
- b)** Distinguish between an electric circuit and a magnetic circuit; stating similarities (04 points) and dissimilarities (02 points) [6]
- c)** Two coils A and B have self-inductances of 10 μH and 40 μH respectively. A current of 2 A in coil A produces a flux a linkage of 5 μWb -turns in coil B. Calculate: [6]
- i) Mutual inductance between the coils
 - ii) Coefficient of coupling
 - iii) Average emf induced in coil B if the current of 1 A in coil A is reversed at uniform rate in 0.1 second.

OR

- Q2) a)** Define Self Inductance by three ways. [3]
- b)** Obtain the expression for energy stored in magnetic field produced by an inductor. [6]
- c)** An iron ring of mean circumference of 150cm and cross sectional area 12 cm^2 is wound with 600 turns of coil. The coil produces flux of 1.25 mWb while carrying a current of 2 A. Find the relative permeability of iron. [6]

- Q3) a)** Define [3]
- i) cycle
 - ii) period and
 - iii) frequency of an alternating quantity.

P.T.O.

- b) Explain the concept of lagging taking two electrical quantities with the help of their waveforms and phasor diagrams. [6]
- c) Two capacitors of $2 \mu\text{F}$ and $8 \mu\text{F}$ are connected in series across 200 V DC supply. [6]

Find

- i) resultant capacitance value
ii) voltage across each capacitor and
iii) charge on each capacitor.

OR

Q4) a) Obtain an expression for average value of a sinusoidal alternating current. [3]

b) Define the following terms in electrostatics and mention their units. [6]

- i) Electric flux density
ii) Electric field strength
iii) Absolute permittivity

c) An alternating current varying sinusoidally with a frequency of 50 Hz has an rms value of 10 A. Write the expression for instantaneous value of this current quantity and find its value for [6]

- i) $t = 0.0015 \text{ sec}$
ii) $t = 0.0075 \text{ sec}$ after passing through zero and then increasing negatively.

✘ ✘ ✘